

iligero LH03



頭燈說明書

感謝您購買我們的產品!
www.iligero.com

產品特點

1. 造型精緻小巧, 方便隨身攜帶, 多用於日常徒步, 露營, 夜跑, 應急等多種照明用途。
2. 使用Cree XP-G3 白光LED, 3030紅光LED, 3030綠光LED, 白光壽命50000小時。
3. 標配1個1100mAh鋰聚合物電池; 兼容3節AAA鎳氫/鹼性電池。
4. 雙開關控制, 操作簡單快捷。
5. 3種亮度選擇及紅光、綠光。
6. Type-C充電接口, 5V/1A充電。
7. 四檔藍光燈電量顯示。
8. 尺寸: 57毫米(長) × 37毫米(寬) × 44毫米(高)。
9. 淨重76克(含電池、含頭燈帶)。



流明與續航

FL1 STANDARD	高亮檔	中亮檔	低亮檔	紅燈	綠燈
☀️ 亮度	400流明	150流明	90流明	/	/
🕒 續航時間	3小時	4.5小時	6小時	/	/
📏 射程	80米				
➕ 最大光強	1600坎德拉				
✓ 防跌落高度	1米				
🌧️ 防水等級	IPX4				

注: 以上資料是使用1顆1100mAh鋰聚合物電池包在實驗室環境下測試得出, 資料可能會因不同品牌的電池或使用環境的變化而有所不同。
* 高亮檔續航時間是累計續航。

操作說明

開機/關機

(聚光顯示) 主按鍵: 開/關機、檔位切換。

(泛光顯示) 輔按鍵: 開/關機、紅綠光模式下檔位切換。

模式切換

開機狀態下, 按一下聚光/泛光按鍵, 即可切換到聚光模式/低亮檔/泛光模式/綠光檔。

檔位切換

聚光按鍵: 按一下聚光按鍵, 即可按低亮→中亮→高亮→關機的順序調節亮度。

泛光按鍵: 按一下泛光按鍵, 即可按綠光→紅光→紅光閃的順序。

電池選用

電池類型	尺寸規格	標稱電壓	是否使用
1100mAh 鋰聚合物電池	44x31x11 mm	3.7V	推薦
鎳氫電池	AAA	1.2V	可用(不可充電)
鹼性電池	AAA	1.5V	可用(不可充電)

警告: 請勿對鎳氫/鹼性電池進行充電, 長時間不用頭燈時, 請每四個月對鋰聚合物電池包充滿電一次, 以防電池漏液操作, 造成設備損壞; 請不要將AAA電池長期置於燈體內。

電池更換

1. 打開後蓋。
2. 按照正負極標識正確裝入電池。
3. 扣緊後蓋即可。

充電說明

1. 可對自帶鋰電池包進行充電, 對於鹼性、鎳氫等AAA電池請勿充電。
2. 打開USB膠帽, 將TYPE-C充電線插入頭燈的充電插口。
3. 開機狀態下充電時, 對於1100mAh鋰聚合物電池包, 從沒電到完全充滿的時間約為2.5小時。
4. 充電完成後, 將USB膠帽蓋回按緊。

電量顯示

筒身有4顆LED顯示燈, 開機後指示燈顯示當前電量

- 4 LED - 剩餘電池電量超過 75%
- 3 LED - 剩餘電池電量 50%

- 2 LED - 剩餘電池電量 25%
 - 1 LED - 剩餘電池電量少於 10% 需及時充電
- * 僅對標配的鋰聚合物電池包有效。

使用與維護

1. 請勿拆卸燈具密封部件, 否則將會導致保修失效並可能損壞燈具。
2. 長期不使用時請將電池從燈具中取出, 否則可能因部分品質不良的電池漏液造成燈具損壞。
3. 請經常清潔燈具或電池的導電接觸面以保證燈具的正常工作, 特別是當燈具出現異常的閃爍或者無法點亮時, 請先檢查電池電量, 再使用酒精棉簽清潔導電接觸面或接觸點。

包裝清單

頭燈、1100mAh鋰聚合物電池包、戶外收納袋、充電線、說明書

注意事項

1. 此燈具光線明亮, 直接照射眼睛可能會導致暫時或長期失明。請勿將本燈具直接照射眼睛!
2. 如果操作不當, 鋰電池可能會洩漏、爆炸造成傷害。請勿將電池暴露在水、高溫或火中。
3. 此燈具長時間使用可能會變熱。操作時請小心, 以防燙傷。
4. 請勿在易燃材料周圍或爆炸性環境中操作。
5. 請將本品放置於兒童接觸不到的地方。

保修條款

1. ILIGERO產品自售出之日起7日內, 在正常使用情況下, 出現產品品質問題, 用戶可選擇更換新品或修理服務, 如同型號同規格的產品停止生產, 可更換不低於原產品性能的同品牌產品。
2. ILIGERO產品自售出之日起1年內, 在正常使用情況下, 出現產品品質問題, 享受免費維修服務。買家將負責商品的運輸。超過12個月, 買家將負責產生的零件和運輸費用。iligero將使用合理的運輸方式寄貨。

下面情況不在保修範圍

1. 損壞、拆卸、毀壞和未經授權的改裝。
2. 因儲存不當或電池洩漏造成的損壞。

售后

請聯繫經銷商處理或發送郵件至info@iligero.com聯繫我們。



iligero LH03



Operation Manual

Thank you for choosing our products!
www.iligero.com

Features

1. Lightweight and easy for daily carry. Specially designed for hiking, camping, night running and emergency use.
2. Cree XP-G3 white, 3030 red and 3030 green LED's, white LED with a lifespan of 50,000 hours.
3. Powered by a 1100mAh Li-polymer battery pack; compatible with 3 AAA Ni-MH/Alkaline batteries (charging prohibited)
4. Dual switches for easy and fast operation.
5. Three brightness levels, max output of 1100 lumen, and green and red lights.
6. USB-C charge port integrated into body of flashlight for quick, convenient charging.
7. 4 green LEDs power Indicator, know battery level at anytime
8. Size: 57mm*37mm*44mm
9. Weight: 76 grams (with battery and head band)



Output & Runtime

FL1 STANDARD	High	Middle	Low	Red	Green
☀️	400 LUMENS	150 LUMENS	90 LUMENS	/	/
🕒	3h	4.5h	6h	/	/
📏	80 meters				
➕	1600cd (Max Intensity)				
✓	1 (Impact Resistant)				
🌧️	IPX4 (Waterproof)				

Note: Stated data has been measured by using one 1100mAh Li-polymer battery pack in the laboratory. The data may vary due to different battery and different environment conditions.
* The High output is measured in total of runtime.

Operating Instruction

ON/OFF

Click the spotlight switch to turn on the light.

Click the floodlight switch to turn on the Green light.

With the light turned on, press the spotlight the cycle through Low-Mid-High-Off

Mode Switching

With the lamp turned on, single click either of the two switches to reach the corresponding mode.

Output Selection

Spotlight mode: single click the spotlight switch to cycle through Low→Mid→High→Off.

Floodlight mode: single click the floodlight switch to cycle through Green→Red→Red flash.

Recommended batteries

Type	Dimensions	Nominal Voltage	Usability
1100mAh Li-polymer battery pack	44x31x11 mm	3.7V	Recommended
Ni-MH Battery	AAA	1.2V	Usable (No charging)
Alkaline Battery	AAA	1.5V	Usable (No charging)

Battery Replacement

1. Open the tail cap.
2. Insert the battery/batteries in accordance with the polarity marks.
3. Replace the tail cap.

Charging

1. The included Li-polymer battery pack can be charged via the headlamp. It is strictly prohibited to charge non-rechargeable AAA (Ni-MH/Alkaline) batteries via the headlamp.
2. Open the USB cover and plug the USB-C cable.
3. The normal charging time of the included Li-polymer battery pack is about 2.5 hours with the lamp being switched off.
3. Once charging is completed, close the dust cover tightly.

Power Indication

When the lamp is on, 4 green indicating LEDs on the head will illuminate to indicate the current battery level.

- 4 LEDs - More than 75% Battery Power remaining
- 3 LEDs - 50% Battery Power Remaining
- 2 LEDs - 25% Battery Power Remaining
- 1 LED - Less than 10% Battery Power Remaining and needs recharging.

Storage and Maintenance

1. Disassembling the sealed head can cause damage to the lamp and will void the warranty.
2. Remove the battery if light will not be used for an extended period.
3. Periodic cleaning of the battery contacts improves the lamp's performance as dirty contacts may cause the lamp to flicker, shine intermittently or even fail to illuminate, please check the battery power first, then clean the contact points with a cotton swab soaked in rubbing alcohol.

IN THE BOX

Iligero LH03 headlamp, 1100mAh Li-ion battery pack, Storage bag, USB-C Charging Cable, User manual

Caution

1. This lamp produces extremely bright light which can cause temporary or prolonged blindness. Never shine light into the eyes of non-adversarial parties.

2. Lithium batteries can leak, explode, and/or cause injury if improperly handled. Do not expose batteries to water, high temperatures, or fire.
3. This lamp may become hot with extended use. Exercise caution when handling to prevent burns.
4. Do not operate around flammable materials or in explosive environments.
5. Keep away from children.

Warranty

1. Iligero will replace identical or equal products with documented manufacturing within 7 days of purchase.
2. Iligero offers a 12 month (1 year) free warranty service from date of purchase. Buyer will be responsible for shipping of the item. Over 12 months, buyer is responsible for incurred parts and shipping costs. Iligero will return using a reasonable shipping method.

Unwarrantable

1. Damage, disassembly, destruction and unauthorized modifications.
2. Damage due to improper storage or battery leakage.

Service

1. Contact your retailer or email us at info@iligero.com.



www.iligero.com MADE IN PRC